

The PA1M30M100V6 is a 100-watt, high-performance broadband power amplifier covering 1 – 30 MHz, designed for CW, AM, FM, Pulse, and general RF applications.

Leveraging advanced Gallium Nitride (GaN) technology, the amplifier delivers a minimum saturated output power of 50 dBm and a minimum small-signal gain of 50 dB with  $\pm 2$  dB gain flatness. Built-in protection, monitoring, and control circuits ensure long-term reliability and repeatable performance across temperature and load conditions.

The unit is supplied in a rugged 4U rack-mount enclosure, with N-Type female connectors for input and output, and is compatible with RS-232/RS-485/RS-422/USB/Ethernet interfaces (customer choose) for control and telemetry. Designed for indoor use, an optional outdoor hub-mount version is available on request.

## Product Features:

- Minimum Small-Signal Gain: 50 dB
- Minimum Saturated Output Power: 50 dBm (100 W)
- Gain Flatness:  $\pm 2$  dB
- Adjustable Gain Range: 20 dB (1 dB steps)
- Instant-On Operation (no warm-up)
- 50  $\Omega$  Matched Input and Output
- Input/Output Connectors: N-Type Female
- Comprehensive Protections:
  - Reverse Polarity
  - Temperature Over-Limit
  - Current Limiting
- Integrated Monitoring and Telemetry:
  - Temperature Indication
  - Current Consumption Monitoring
- Control Interfaces: RS-232 / RS-485 / RS-422 / USB / Ethernet (customer selectable)
- Power Input: 100–240 VAC, 50/60 Hz
- Solid-State MMIC Reliability
- Rack-Mountable (3U, 50 cm depth)



### Application:

- Radar Transmitters
- Satellite Communication Systems
- TWTA Replacement
- R&D and Laboratory Use
- Jamming
- Military and Aerospace Platforms

### Electrical Specifications ( $T_A=+25^{\circ}\text{C}$ )

Parameter	Typ	Units
Frequency Range	1 – 30	MHz
Minimum Small Signal Gain (0 dBm input)	50	dB
Minimum Saturated Output Power (Psat)	100	W
Gain Variance (Maximum)	+/-2	dB
Gain Variation Over Temperature (-40°C to +70°C)	+/-3	dB
Gain adjustment range	20	dB
Gain adjustment step size	1	dB
Input Return Loss	-15	dB
Spurious	-60	dBc
Harmonics @ POUT = 100W	-20 (2 <sup>nd</sup> ) -10 (3 <sup>rd</sup> )	dBc
IM3	-20	dBc
Noise Figure @ max. gain	10	dB
Input RF drive level without damage	+ 10 (Max)	dBm
Operating voltage	100 to 240	VAC
Supply Current	2	A
Weight	8	Kg
Impedance	50	Ohms
Size	3U rack, 50cm deep	
Input / Output Connectors	N-Type Female	
Monitoring and control interface	D-SUB, 9-pin, Male	
AC Power connector	IEC 60320-C14	

## Environmental Specifications and Test Standards

Parameter	Description
Operational Temperature	-40°C to +85°C (Case Temperature)
Storage Temperature	-40°C to +85°C
Thermal Shock	-40°C to +85°C (5 Cycles / 10 hours)
Random Vibration	MIL-STD-202G Table 214-I, Test Condition Letter C; 1.5 Hours Per Axis
High-Temperature Burn-In	Temperature +85°C for 72 Hours
Shock	1. Weight >20g, 50g half sine wave for 11ms, Speed variation 3.44m/s 2. Weight ≤20g, 100g Half sine wave for 6ms, Speed variation 3.75m/s 3. Total 18 times (6 directions, 3 repetitions per direction).
Altitude	Standard: 30,000 Ft (Epoxy Sealed Controlled Environment) Optional: Hermetically Sealed (60,000 ft. 1.0 PSI min)

## Handling Precautions



Caution!  
ESD-Sensitive Device

**RF VOLTAGE HAZARD:** Contact with RF fields at the output connector can cause burns or electric shock. High levels of RF/Microwave energy may be present when the unit is operating.

**HIGH DC CURRENT HAZARD:** High levels of DC current are present when the unit is operating.

Each amplifier is shipped in a hard and well-protected carry case.





# Solid State Power Amplifier 100W 1MHz to 30MHz

Part No.: PA1M30M100V6

## Contact Information

---

For the latest specifications, additional product information, worldwide sales and distribution locations:

Web: [www.poamelectronics.com](http://www.poamelectronics.com)

Tel: +44 (0) 161 52 64 551

Email: [sales@poamelectronics.com](mailto:sales@poamelectronics.com)

## Important Notice

---

The information contained herein is believed to be reliable; however, POAM makes no warranties regarding the information contained herein and assumes no responsibility or liability whatsoever for the use of the information contained herein. All information contained herein is subject to change without notice. Customers should obtain and verify the latest relevant information before placing orders for POAM products. The information contained herein or any use of such information does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other intellectual property rights, whether with regard to such information itself or anything described by such information. THIS INFORMATION DOES NOT CONSTITUTE A WARRANTY WITH RESPECT TO THE PRODUCTS DESCRIBED HEREIN, AND POAM HEREBY DISCLAIMS ANY AND ALL WARRANTIES WITH RESPECT TO SUCH PRODUCTS WHETHER EXPRESS OR IMPLIED BY LAW, COURSE OF DEALING, COURSE OF PERFORMANCE, USAGE OF TRADE OR OTHERWISE, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

Without limiting the generality of the foregoing, Poam products are not warranted or authorized for use as critical components in medical, life-saving, or life-sustaining applications or other applications where a failure would reasonably be expected to cause severe personal injury or death.

Copyright 2025 © POAM, Ltd. | POAM is a registered trademark of POAM Electronics Ltd.

Data Sheet Rev. B, Jan. 2025 Subject to change without notice.

[www.poamelectronics.com](http://www.poamelectronics.com)